



	Worldwide except USA/Canada Japan	USA/Canada Japan
	** PE (earth)	Green/Yellow
	Neutral	Blue
	Phase	Brown
	Or Talk	White
	Alarm contact wires	Black
	Screen(Scn) Shrink sleeve	A Orange
		B Yellow
	Common: Red	
	NC: Purple	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
L	N	PE	C	NC	L	N	PE	A	B	SCN	C	NC	L	N	PE	A	B	SCN	C	NC
Power Input	Alarm Out				Power Output	OrTalk	Alarm IN						Power Output	OrTalk	Alarm IN					

Terminal



Warning: Make sure that the mains power supply is disconnected before you start the electrical installation.



Note: Make sure that the OVP-S30 has enough service space and enclosure is correct levelled.

** Replace default PE Eyelet by wire ferrule for PE Terminal. All dimensions are in millimeters (mm) unless otherwise noted.